DESCRIPTIONS

AC-DC 240W DIN-Rail Power Supply



RoHS

CE Report EN62368-1

UKCA Report BS EN62368-1

FEATURES

- Universal 85 - 277VAC or 120 - 390VDC Input voltage
- Operating ambient temperature range: -40℃ to +85℃, full load at 60℃
- High efficiency, high reliability
- Transient peak current function: 6 times rated current for 15ms
- Up to 200% (PN) dynamic power for 5s
- Continuous static power margin of up to 125% (PN)
- Support 5+1 bus high precision parallel current sharing
- Active PFC, PF > 0.98
- Support DC OK, AC OK, remote control function
- Support ModBus communication protocol
- Double-sided conformal coating, salt-spray proof, explosion-proof
- Operating altitude up to 5000m
- OVC III (design refer to EN62477, 2000m)
- OVC II
- Pollution degree 2
- 5 years warranty
- Output short circuit, over-current, over-voltage, over-temperature protection, input under voltage protection
- Safety according to ATEX, IECEx increased safety type explosion-proof certification
- Safety according to ANSI/ISA 71.04-2013 G3
- Safety according to IEC/UL62368, GB4943, IEC/EN61010, EN61558, EN62477, IEC60079, GB3836, NB/T31017

APPLICATIONS

- Wind power industry
- Ships
- DCS
- Industrial control equipment
- Imachine control
- Instrumentation
- LED
- Power
- Security
- 5G communication
- New energy

Selection Guide

Certification	Part No.*	Output Power (W)	Nominal Output Voltage and Current (Vo/Io)	Output Voltage Adjustable Range (V)	Efficiency at 230VAC (%) Typ.	Max. Capacitive Load (μF)
EN/BS EN	ADHF240-2B-24	240	24V/10A	24-28	94.5	50000
	ADHF240-2B-48		48V/5A	48-55	95	25000

Note: 1.*When the output voltage rises, the total power of the product should not exceed the rated power;
2.*The product picture is for reference only, for details, please refer to the actual product.

Specifications

Product Specifications	Item	Operating Conditions		Min.	Typ.	Max.	Unit
Input Specifications	Input Voltage Range	Rated input (Certified voltage)		100	--	240	VAC
		AC input		85	--	277	
		DC input		120	--	390	VDC
	Maximum Input Voltage	Lasts for 2h without damage		--	--	305	VAC
	Input Voltage Frequency			47	--	63	Hz
	Input Switching Voltage			65	--	80	VAC
	Input Turn-off Voltage			55	--	70	
	Input Current	115VAC		--	--	3	A
		230VAC		--	--	1.5	
	Inrush Current	115VAC	Cold start	--	10	--	
		230VAC		--	15	--	
	Power Factor	115VAC		0.98	--	--	--
		230VAC		0.95	--	--	
	THD	115VAC, rated load		--	3.5	--	%
	Start-up Delay Time	115VAC/230VAC, rated load		--	--	2000	ms
	Input Fuse	Built-in fuse		--	8	--	A
	Hot Plug			Unavailable			
Output Specifications	Output Voltage Accuracy	Full load range		--	±1.0	--	%
	Line Regulation	Rated load		--	±0.25	--	
	Load Regulation	0% - 100% load		--	±0.5	--	
	Power Consumption*	230VAC, rated load	24V	--	13.9	--	W
			48V	--	12.6	--	
	Ripple & Noise*	20MHz bandwidth, peak-to-peak value	24V	--	--	80	mV
			48V	--	--	120	
	Hold-up Time	115VAC/230VAC		20	--	--	ms
	DC OK Signal	Resistive load		30VDC/1A Max.			
	Short Circuit Protection			Hiccup mode, constant current operation(constant current time adapts with different load conditions), output off for 5s, long-term short-circuit protection, self-recover			

	Static power		115VAC/230VAC		125%Io (typ.), work for a long time at room temperature			
	Dynamic power				200% Io working 5s (min.), the off time adapts with different load conditions, long-term protection, self-recover			
	Transient Peak Current Function				600% Io working 15ms 3 times (typ.), long-term short-circuit protection, self-recover			
	Over-voltage Protection		24V		≤35VDC (Output-off or clamping, self-recover)			
			48V		≤60VDC (Output-off or clamping, self-recover)			
	Over-temperature Protection*		230VAC, rated load, self-recover	Over-temperature protection start	--	--	95	℃
				Over-temperature protection release	60	--	--	
General Specifications	Isolation Test*	Input - ⏚	Electric strength test for 1min., leakage current <5mA (Isolation Test for ⏚ need to remove the screw at the mark shall ⚙ *)		2500	--	--	VAC
		Input - output			4000	--	--	
		Output - ⏚			500	--	--	
	Insulation Resistance	Input - ⏚	Environment temperature: 25±5℃ Relative humidity: < 95%, non-condensing Test voltage: 500VDC		500	--	--	MΩ
		Input - output				--	--	
		Output - ⏚				--	--	
	Operating Temperature				-40	--	+85	℃
	Storage Temperature				-40	--	+85	
	Operating Humidity		Non-condensing		10	--	95	%RH
	Storage Humidity				20	--	90	
	Switching Frequency*		PFC		60	--	70	kHz
			DC-DC		40	--	130	
	Power Derating		Operating temperature derating @AC input	-40℃ to -30℃	2	--	--	%/℃
				+60℃ to +75℃	2.5	--	--	
				+75℃ to +85℃ 25CFM	2.25	--	--	
			Operating temperature derating @DC input	-40℃ to -30℃	2	--	--	
				+60℃ to +75℃	2.5	--	--	
				+75℃ to +85℃ 25CFM	2.25	--	--	
			Input voltage derating	85VAC - 100VAC	1	--	--	%/VAC
				120VDC - 140VDC	1	--	--	%/VDC
	Leakage Current		240VAC	Touch current	< 0.5mA			
	Safety Class				CLASS I			
	MTBF		MIL-HDBK-217F@25℃		> 702,000h			

		MIL-HDBK-217F@40℃		> 524,000h			
	OVC			III			
	Warranty	Ambient temperature: <40℃		5 years			
	High and Low Voltage Crossing	It needs to be test with UPS (TBD)		NB/T 31111-2017			
Functional Specifications	Remote control	Voltage between ON/OFF and SGND	Power on	0	--	0.8	VDC
			Power off	4	--	20	
	DC OK Relay	Operation voltage	24V	--	21.6	--	V
			48V	--	43.2	--	
		Release voltage	24V	--	19.2	--	
			48V	--	38.4	--	
	AC OK signal	Input voltage 85 - 305VAC		3	--	5	VDC
	Current Sharing Accuracy	When multiple units are connected in parallel, the sub-modules shunt more than 50% of the rated load of a single power supply		--	±5	--	%
	LED signal	Main output status indicator	Normal output	LED ON			
			200%Io > Load > 125%Io	Green light flashing			
			Power off (No AC power), under-voltage protection, remote off, short circuit/over-current protection, output voltage backflow	LED OFF			
	RS485-A, RS485-B	Based on ModBus communication protocol		RS485 communication			
Environmental Characteristics	Item	Operating Conditions		Standard			
	High and Low Temperature Working	+85℃, -40℃		GB2423.1, IEC60068-2-1			
	Sinusoidal Vibration	10 - 500Hz, 2g, three directions of X, Y, Z axis		GB2423.10, IEC60068-2-6			
	Salt Mist	+35℃, 5%NACL, 48h		GB2423.17, IEC60068-2-11			
	Alternating Hot and Humid	+25℃, 95%RH - +60℃, 95%RH		GB2423.4, IEC60068-2-30			
	Low Temperature Storage	-40℃		GB2423.1, IEC60068-2-1			
	High Temperature Storage	+85℃		GB2423.2, IEC60068-2-2			
	High Temperature Aging	+60℃		GB2423.2, IEC60068-2-2			
	Normal Temperature Aging	+25℃		GB2423.1, IEC60068-2-1			
	Temperature Shock	-40℃ to +85℃		GB2423.22, IEC60068-2-14			
	Temperature Cycle	-25℃ to +60℃		GB2423.22, IEC60068-2-14			
	Hot and Humid	+85℃, 85%RH		GB2423.50, IEC60068-2-67			
	High Temperature Elevation	+60℃, 54KPa		GB2423.26, IEC60068-2-41			
	Low Temperature Elevation	-25℃, 54KPa		GB2423.25, IEC60068-2-40			
	Constant Humid and Hot	+40℃, 95%RH		GB2423.3, IEC60068-2-78			

	Random Vibration	5 - 10Hz, ASD 0.3 - 10g²/Hz, three directions of X, Y, Z axis	GB/T 4798.2-2008, IEC60721-3-2
	Sinusoidal Vibration Response	10 - 150Hz, 1g, three directions of X, Y, Z axis	GB/T 11287-2000, IEC60255-21-1
	Sinusoidal Vibration Endurance Test		
	Sinusoidal Impulse Response	15g, pulse duration 11ms, three times in each direction of X, Y, Z axis	GB/T 114537-1993, IEC60255-21-2
	Sinusoidal Impact Endurance Test		
	Packaging Drop	1m, one corner, three edges and six sides	GB2423.8, IEC68-2-32
Mechanical Specification	Case Material	Metal (AL5052, SUS304)	
	Dimensions	125.00mm × 130.00mm × 50.00mm	
	Weight	950g (Typ.)	
	Cooling Method	Free air convection	

Note:

1. *The "Tip and barrel method" is used for ripple and noise test, output parallel 47uF electrolytic capacitor and 0.1uF ceramic capacitor;
2. *Over-temperature protection: Put the product into a high temperature box. After the ambient temperature stabilizes, increase the temperature slightly (3℃ to 5℃), and the load remains unchanged. After the product reaches thermal equilibrium, increase the temperature until the product triggers over-temperature protection;
3. *Power consumption curve, over-current protection mode and short circuit protection mode see product characteristic curve.
4. * ①Remove the screw at the mark ⏚ when the product is subjected to withstand voltage test; ② The gas discharge tube built into the device effectively protects the power supply against damage by asymmetric disturbance variables (eg EN 61000-4-5). Each power supply continuous withstand voltage test will cause extremely high load to the power supply. Therefore, unnecessary loading or damage to the power supply due to excessive test voltage should be avoided. If necessary, disconnect the gas discharge tube built into the device to use a higher test voltage. After successful completion of the test, reconnect the gas discharge tube. Please refer to the "ADHF240-2B-xx series power supply application manual" for specific operation methods;
5. * The power supply has two converters with two different switching frequencies, Intermittent operation mode will be entered in light load or no load.
6. *Please refer to ADHF240-2B-xx Series Power Supply Application Manual for related functions, LED signal, control logic and usage instructions.;
7. *When multiple prototypes are working in uniform current, the output voltage deviation of each prototype working separately shall not exceed 100mV.
8. When the remote control terminal is suspended, the output voltage of the power supply is output normally

Electromagnetic Compatibility (EMC)

Electromagnetic Compatibility (EMC)	EMI	CE	General standard	CISPR32 EN55032 CLASS B
			Industry/Light industry	IEC61000-6-3 AC port CLASS B, DC port CLASS A
				IEC61000-6-4 AC port CLASS A
			Classification society*	GD22-2015 10kHz - 30MHz, EMC1
			Power station/Subsation	IEC61850-3 CLASS A
			Railway	IEC62236-3-2 (EN50121-3-2) Output port CLASS A +20dB
				IEC62236-4 (EN50121-4) Output port CLASS A +20dB
				IEC62236-5 (EN50121-5) AC port CLASS A
		RE	General standard	CISPR32 EN55032 CLASS B
			Industry/Light industry	IEC61000-6-3 CLASS B
				IEC61000-6-4 CLASS A
			Classification society	GD22-2015 150KHz - 2GHz, EMC1

Electromagnetic Compatibility (EMC)			Power station/Subsation	IEC61850-3 CLASS A	
			Railway	IEC62236-3-2 (EN50121-3-2) CLASS B	
				IEC62236-4 (EN50121-4) CLASS B	
				IEC62236-5 (EN50121-5) CLASS B	
		Harmonic current	General standard	IEC/EN6100-3-2 Class A and Class D	
			Railway	IEC62236-3-2 (EN50121-3-2) 50Hz - 2KHz	
				IEC62236-4 (EN50121-4) 50Hz - 2KHz	
	EMS	ESD	General Standard	IEC/EN 61000-4-2 Output port Contact ±8KV/Air ±15KV	perf. Criteria A
			Industry/Light industry	IEC61000-6-1 Contact ±4KV/Air ±8KV	perf. Criteria A
				IEC61000-6-2 Contact ±4KV/Air ±8KV	perf. Criteria A
			Wind power	NB/T 31017-2011 Contact ±6KV/Air ±8KV	perf. Criteria A
			Classification society	GD22-2015 Contact ±6KV/Air ±8KV	perf. Criteria A
			Power station/Subsation	IEC61850-3 Contact ±6KV/Air ±8KV	perf. Criteria A
				IEC61000-6-5 Contact ±6KV/Air ±8KV	perf. Criteria A
			Railway	IEC62236-3-2 (EN50121-3-2) Contact ±6KV/Air ±8KV	perf. Criteria A
				IEC62236-4 (EN50121-4) Contact ±6KV/Air ±8KV	perf. Criteria A
				IEC62236-5 (EN50121-5) Contact ±6KV/Air ±8KV	perf. Criteria A
	EMS	RS	General standard	IEC/EN 61000-4-3 10V/m	perf. Criteria A
			Industry/Light industry	IEC61000-6-1 80M - 1GHz, 3V/m; 1.4G - 6GHz, 3V/m	perf. Criteria A
				IEC61000-6-2 80M - 1GHz, 10V/m; 1.4G - 2GHz, 3V/m; 2 - 2.7GHz, 1V/m	perf. Criteria A
			Wind power	NB/T 31017-2011 80M - 1GHz, 10V/m	perf. Criteria A
			Classification society	GD22-2015 80M - 2GHz, 10V/m	perf. Criteria A
			Power station/Subsation	IEC61850-3 80M - 3GHz, 10V/m	perf. Criteria A
				IEC61000-6-5 80M - 1GHz, 10V/m; 1G - 2.7GHz, 3V/m; 2.7G - 6GHz, 1V/m	perf. Criteria A
			Railway	IEC62236-3-2 (EN50121-3-2) 80M - 1GHz, 20V/m; 1.4GHz - 2GHz, 10V/m; 2G - 2.7GHz, 5V/m; 2.7G - 6GHz, 3V/m	perf. Criteria A
				IEC62236-4 (EN50121-4) 80M - 800MHz, 10V/m; 800MHz - 1GHz, 20V/m; 1.4G - 2GHz, 10V/m; 2G - 2.7GHz, 5V/m; 5.1G - 6GHz, 3V/m	perf. Criteria A
				IEC62236-5 (EN50121-5) 80M - 800MHz, 10V/m; 800MHz - 1GHz, 20V/m; 1.4G - 2GHz, 10V/m; 2G - 2.7GHz, 5V/m; 5.1G - 6GHz, 3V/m	perf. Criteria A
		EFT	General standard	IEC/EN 61000-4-4 ±4KV	perf. Criteria A
			Industry/Light industry	IEC61000-6-1 DC input, output and signal contral port: ±0.5KV, 5/100KHz, AC input and output port: ±1KV, 5/100KHz	perf. Criteria A

Electromagnetic Compatibility (EMC)				IEC61000-6-2 DC input, output and signal contral port: ±0.5KV, 5/100KHz, AC input and output port: ±1KV, 5/100KHz	perf. Criteria A
			Wind power	NB/T 31017-2011 Power source and PE: ±4KV, 5/100KHz, signal and contral port: ±2KV, 5/100KHz (Capacitive coupling clamp)	perf. Criteria A
			Classification society	GD22-2015 ±1KV, 5KHz; ±2KV, 2.5KHz	perf. Criteria A
	EMS	EFT	Power station/Subsation	IEC61850-3 AC, DC input output port, signal port, ground port: ±2KV	perf. Criteria A
				IEC61000-6-5 AC, DC input output port: ±2KV; signal port: cable < 3m: ±2KV, cable > 3m: ±4KV	perf. Criteria A
			Railway	IEC62236-3-2 (EN50121-3-2) Signal, contral port: ±2KV, 5KHz (Capacitive coupling clamp), AC, DC input output port: ±2KV, 5KHz	perf. Criteria A
				IEC62236-4(EN50121-4) Signal, contral port: ±2KV, 5KHz (Capacitive coupling clamp), AC, DC input output port: ±2KV, 5KHz, PE ground/shell: ±1KV, 5KHz	perf. Criteria A
				IEC62236-5(EN50121-5) Signal, contral port: ±2KV, 5KHz Capacitive coupling clamp), AC, DC input output port: ±4KV, 5KHz, PE ground/shell: ±1KV, 5KHz	perf. Criteria A
		Surge	General standard	IEC/EN 61000-4-5 AC input port: ±3KV/±6KV	perf. Criteria A
			Industry/Light industry	IEC61000-6-1 DC input and output port: ±0.5KV/±1KV, AC input and output port: ±1KV/±2KV, signal and contral port: ±1KV common mode	perf. Criteria A
				IEC61000-6-2 DC input and output port: ±0.5KV/±0.5KV, AC input and output port: ±1KV/±2KV, signal and contral port: ±1KV common mode	perf. Criteria A
			Wind power	NB/T 31017-2011 AC, DC power source port: ±1KV/±2KV	perf. Criteria A
			Classification society	GD22-2015 AC, DC power source port: ±0.5KV/±1KV	perf. Criteria A
			Power station/Subsation	IEC61850-3 AC, DC power source, signal port: ±1KV/±2KV, power carrier communication port: ±2kV/4kV	perf. Criteria A
			Power station/Subsation	IEC61000-6-5 Signal, contral port: ±1KV common mode (If the cable < 10m, no test is required), DC input and output port: ±1KV/±2KV, AC input and output port: ±2KV/4KV	perf. Criteria A
			Railway	IEC62236-3-2 (EN50121-3-2) Battery port, AC input port: ±1KV/±2KV (42Ω output impedance)	perf. Criteria A
				IEC62236-4 (EN50121-4) DC power source, signal,	perf. Criteria A

Electromagnetic Compatibility (EMC)				contral port: ±1KV/±2KV (42Ω output impedance), AC power source port: ±1KV/±2KV	
				IEC62236-5 (EN50121-5) DC input and output, signal, contral port: ±1KV/±2KV, AC input and output port: ±2KV/±4KV	perf. Criteria A
		CS	General standard	IEC/EN61000-4-6 10Vr.m.s	perf. Criteria A
			Industry/Light industry	IEC61000-6-1 AC input and output, signal, contral port: 0.15M - 80MHz, 3V	perf. Criteria A
				IEC61000-6-2 AC input and output, signal, contral port: 0.15M - 80MHz, 10Vr.m.s	perf. Criteria A
	EMS	CS	Wind power	NB/T 31017-2011 0.15M - 80MHz, 10Vr.m.s	perf. Criteria A
			Classification society	GD22-2015 0.15M - 80MHz, 10Vr.m.s, Low frequency conduction immunity: AC input port, harmonic < 15 times 10%Un, harmonic = 15 - 100 times, from 10%Un to 1%Un, harmonic = 100 - 200 times, 1%Un; DC input port, 10%Un, 50 - 10kHz, apply power≤2W (The applied voltage can be reduced)	perf. Criteria A
			Power station/Subsation	IEC61850-3 AC, DC input, output, signal, contral port, PE port: 0.15M - 80MHz, 10Vr.m.s	perf. Criteria A
				IEC61000-6-5 AC, DC input, output, signal, contral port: 0.15M - 80MHz, 10Vr.m.s	perf. Criteria A
			Railway	IEC62236-3-2 (EN50121-3-2) AC/Battery input, signal, contral port: 0.15M - 80MHz, 10Vr.m.s	perf. Criteria A
				IEC62236-4 (EN50121-4) AC, DC input, output, signal, contral port: 0.15M - 80MHz, 10Vr.m.s	perf. Criteria A
				IEC62236-5 (EN50121-5) AC, DC input, output, signal, contral port, PE port: 0.15M - 80MHz, 10Vr.m.s	perf. Criteria A
		Voltage dips, short interruptions and voltage variations immunity	General standard	IEC/EN61000-4-11 0%, 70%	perf. Criteria B
			Industry/Light industry	IEC61000-6-1 0%, 0.5/1 period, 70%, 25/30 period @50/60Hz, 0%, 250/300 period @50/60Hz	perf. Criteria B and C
				IEC61000-6-2 0%,1 period, 0%, 250/300 period @50/60Hz, 40%, 10/12 period @50/60Hz	perf. Criteria B and C
			Power station/Subsation	IEC61850-3 AC input and output port: 100%, 5/50 period, DC input and output port: 100%, 0.05s	perf. Criteria B
				IEC61000-6-5 AC input and output port: 70%, 1 period, 40%, 50 period, 0%, 5 period, 0%, 50 period	perf. Criteria B
		Power frequency magnetic field	General standard	IEC/EN61000-4-8 100A/mcontinuous, 1KA/m 1s	perf. Criteria A
			Industry/Light industry	IEC61000-6-1 50/60Hz, 30A/m	perf. Criteria A
				IEC61000-6-2 50/60Hz, 30A/m	perf. Criteria A
			Power station/Subsation	IEC61850-3 100A/mcontinuous, 1KA/m 1s	perf. Criteria A
				IEC61000-6-5 100A/mcontinuous, 1KA/m 1s	perf. Criteria A
			Railway	IEC62236-4 (EN50121-4) 50Hz, 100A/m, DC 300A/m	perf. Criteria A
				IEC62236-5 (EN50121-5) 50Hz, 100A/m, DC 300A/m	perf. Criteria A

Note: 1. *perf. Criteria:

A: The equipment shall continue to operate as intended without operator intervention;

B: After the test, the equipment shall continue to operate as intended without operator intervention;

C: Loss of function is allowed, provided the function is self-recoverable, or can be restored by the operation of the controls by the user in accordance with the manufacturer's instructions;

2. *Tested with filter P/N: EFP2I06-CCS.

Characteristic Curve




Figure 1




Figure 2




Figure 3




Figure 4

Over-current/ Short circuit protection curve




Figure 5

Transient peak current curve (Typ.)




Figure 6

AC-OK




Figure 7

DC OK behavior curve (Typ.)




Figure 8

AC VS AC-OK VS Uo




Figure 9

ON /OFF




Figure 10




Figure 11




Figure 12




Figure 13




Figure 14




Figure 15




Figure 16

Note:1. All curves are for 24V output, measured at input 230VAC, 50Hz, output Io, ambient temperature 25℃, unless otherwise stated;

2. With an AC input voltage between 85-100VAC and a DC input between 120 - 140VDC the output power must be derated as per the temperature derating curves;

3. FIG. 1, 2, 4 and 5 are carried out under the condition of 25 CFM at a high temperature of 75 ~ 85℃;

4. This product is suitable for applications using natural air cooling, for applications in closed environment please consult .




Figure 17





Figure 18

Dimensions and Recommended

THIRD ANGLE PROJECTION



Pin–Out	
Pin	Mark
1	–Vo
2	–Vo
3	–Vo
4	+Vo
5	+Vo
6	⏚
7	AC(N)
8	AC(L)

Signal	Pin–Out	
	Pin	Mark
S-1	S–1	DC
S-2	S–2	OK
S-3	S–3	RS485–A
S-4	S–4	RS485–B
S-5	S–5	ON/OFF
S-6	S–6	SGND
S-7	S–7	AC OK
S-8	S–8	PCS
S-9	S–9	PCS

Note:
Unit: mm[inch]
Wire range: Input: 22–10AWG(12–10AWG for pin6)
Output: 24V：14–10AWG
48V：18–10AWG
Signal：24–16AWG
Tightening torque: Max 0.5N・m
Mounting rail: TS35, rail needs to connect safety ground
General tolerances: ± 1.00[± 0.039]

WARNING Risk of electrical shock, fire, personal injury or death:

AVERTISSEMENT AVERTISSEMENT Risque de choc électrique, d'incendie, de blessures corporelles ou de décès :

1. Do not use the power supply without proper grounding (Protective Earth). Use the terminal on the input block for earth connection and not one of the screws on the housing;
   N'utilisez pas l'alimentation électrique sans mise à la terre appropriée (Terre protectrice). Utilisez le terminal sur le bloc d'entrée pour la connexion terrestre et non pas une des vis sur le boîtier;
2. Turn power off before working on the device, protect against inadvertent re-powering;
   Éteignez l'alimentation avant de travailler sur l'appareil, protégez-vous contre la réénergisation accidentelle;
3. Make sure that the wiring is correct by following all local and national codes;
   Assurez-vous que le câblage est correct en suivant tous les codes locaux et nationaux;
4. Do not modify or repair the unit;
   Ne modifiez pas ou ne réparez pas l'appareil;
5. Do not open the unit as high voltages are present inside;
   Ne modifiez pas ou ne réparez pas l'appareil;
6. Use caution to prevent any foreign objects from entering the housing;
   Faire preuve de prudence pour empêcher les objets étrangers d'entrer dans le logement;
7. Do not use in wet locations or in areas where moisture or condensation can be expected;
   Faire preuve de prudence pour empêcher les objets étrangers d'entrer dans le logement;
8. Do not touch during power-on, and immediately after power-off, hot surfaces may cause burns;
   Ne touchez pas pendant l'alimentation et, immédiatement après l'alimentation, les surfaces chaudes peuvent causer des brûlures.
9. For ambient temperature ≤60℃, use ≥90℃ - copper wire only; for ambient temperature >60℃ to 85℃, use ≥105℃ - copper wire only; use only wires with a minimum dielectric strength of 300V (input) and 60V (output);

Température ambiante ≤60℃, utiliser ≥90℃ - seulement fils de cuivre; Température ambiante >60℃ et 85℃, utiliser ≥105℃ - seulement fils de cuivre; Uniquement pour l'ulilisation de fils de cuivre d'une résisitance d'isolation minimale de 300V (d'entrée) et 60V (de sortie).

Note:

1. Unless otherwise specified, parameters in this datasheet were measured under the conditions of Ta=25℃, humidity <75% RH with nominal input voltage and rated output load;
2. The room temperature derating of 5℃/1000m is needed for operating altitude greater than 2000m;
3. All index testing methods in this datasheet are based on our company corporate standards;
4. In order to improve the efficiency at high input voltage, there will be audible noise generated, but it does not affect product performance and reliability;
5. We can provide product customization service, please contact our technicians directly for specific information;
6. Products are related to laws and regulations: see "Features" and "EMC";
7. The out case needs to be connected to PE (⏚) of system when the terminal equipment in operating;
8. Key to adjust, △ key for voltage increase, ▽ key for voltage decrease;
9. Our products shall be classified according to ISO14001 and related environmental laws and regulations, and shall be handled by qualified units.
10. The image certification marks are for reference only; please refer to the selection table for actual specifications. Certification is based on the physical mark or packaging label.

ADHF240-2B-xx Series Power Supply Application Notes

Content

1. Mechanical Specification 17

1.1 Input terminal (CN1) 15

1.2 Output terminal (CN2) 16

1.3 Signal connection terminal (CN5) 16

1.4 Status display LED 17

1.5 Output voltage regulation 17

2. Circuit block diagram 16

3. Function Manual 19

3.1 Input Requirements 19

3.2 Output Requirements 19

3.3 Power Failure Holding Time And AC OK Advance Warning Time 20

3.4 Output Over-Voltage Protection (OVP) 20

3.5 Transient Peak Current Function 22

3.6 Output Over-Current and Short Circuit Protection (OCP And SCP) 22

3.7 Over Temperature Protection (OTP) 22

3.8 Output Power Derating 23

3.9 Remote Control Switch 23

3.10 DC_OK Signal 24

3.11 Used in series 25

3.12 Work in parallel 26

3.13 PC Monitoring 27

3.14 Back Voltage Load 31

4. Installation Requirements 32

4.1 Safety Introduction 32

4.2 Safety Requirements 33

4.3 High-voltage Holding Test 33

4.4 Installation Methods 33

1. Mechanical Specification





Figure 1: ADHF240-2B-xx Appearance Information

Structure Instruction	
1	Input terminal (CN1)
2	Output terminal (CN2)
3	Mode status display LED
4	Voltage adjustment button
5	Signal connection terminal (CN5)
6	Power indicating LED

1.1 Input Terminal (CN1)

3 Position 6.35 mm Barrier Terminal Blocks is used as Input terminal.




Pin	Features
L	Live
N	Neutral
⏚	Protective Earth

Line size: 22-10AWG

Torque: 0.5Nm

1.2 Output Terminal (CN2)

6 Position 6.35 mm Barrier Terminal Blocks is used as Output terminal.




Pin	Features
+Vo	Positive output
-Vo	Negative output

Line size: 14-10 AWG

Torque: 0.5 Nm

1.3 Signal Connection Terminal (CN5)

Signal	Pin-Out	
	Pin	Mark
	S-1	DC
	S-2	OK
	S-3	RS485-A
	S-4	RS485-B
	S-5	ON/OFF
	S-6	SGND
	S-7	AC OK
	S-8	PCS
	S-9	PCS

Line size: 24-16 AWG

Torque: 0.5 Nm

1.4 Status Display LED




Power status indicator LED

LED	State
LED1 ON	DC-OK, Output Power≤50%
LED1-LED2 ON	75%≥Output Power>50%
LED1-LED3 ON	100%≥Output Power>75%
LED1-LED4 ON	Output Power>100%
LED4 Flashing	200%≥Output Power>125%

Mode status indicator


LED	State
LED5 ON	I2x, 2 times peak current
LED6 ON	I6x, 6 times transient peak current

1.5 Output Voltage Regulation



Model	Rated Output Voltage	Output Voltage Adjustable Range
ADHF240-2B-24	24VDC	24VDC-28VDC
ADHF240-2B-48	48VDC	48VDC-55VDC

2. Circuit Block Diagram



3. Function Manual


3.1 Input Requirements

The AC input voltage and DC input voltage must be within the defined voltage range (refer to the data sheet), otherwise the power supply may not work properly or even fail. An 8A/250VAC fuse is connected to the power module. To better protect the power module, you are advised to use a circuit breaker larger than 8A (Strengthen protection, not necessary access requirements).

3.2 Output Requirements

At any output voltage value, if it is necessary to operate normally, the highest pull current and power must not exceed the rated specified value, and the output current must not exceed the maximum output current value.


3.3 Power Failure Holding Time And AC OK Advance Warning Time



Item	Working conditions		Min.	Typ.	Max.	Unit
Power-off hold time	115VAC/230VAC, full load		--	22	--	ms
AC OK Advance warning time	115VAC/230VAC, full load	The warning time is higher than Uo*90%	--	15	--	ms


3.4 Output Over-Voltage Protection (OVP)

The main circuit output will be off when the output voltage reaches the over-voltage protection value. When it occurs, the output enters the hiccup mode with 5s. After the abnormal removed, the output returns to normal.



3.5 Transient Peak Current Function

Transient peak current means that the output can work at 600% Io constant current. When the output is short circuit or needs a lot of current, it can work at 600% Io constant current for 3 times for 15ms (typ.), which can provide long-term short-circuit protection and self-recovery.



Note: The function of the 600% transient peak current function can be turned on or off in the following two ways, with a state of up to 200% current limit after being turned off:

Method 1: Hold down the two buttons of voltage regulation for 3s at the same time, and the LED display changes from I6x to I2x;

If you hold down 3s again, you can turn on the 600% peak current function again.

Method 2: The function can be turned on or off by writing the corresponding instruction to address 65 through Modbus communication:


Site	Data Type	Variable Name	Function Declaration
65	Uint16	Control_Mode	Control mode: 1: Turn on 600% transient peak current 0: Turn off 600% transient peak current

Name	Value	Unit	Read	Command	Write	Block	Address	Count	Offset	Digit	Coefficient
Control Mode	0X0001		Read		Write	RW	65	1	0	16	1

3.6 Output Over-Current And Short Circuit Protection (OCP And SCP)

Static power mode: When the output current exceeds 100% of the rated output current but does not exceed 125% of the rated output current, the output enters the static power mode. The static power of the product is 125%Io (typ.), which can work for a long time and does not enter the protection state.

Dynamic power mode: When the output current exceeds 125% of the rated output current and does not exceed 200% of the rated output current, the output will enter the dynamic power mode. The dynamic power point of the product is 200%Io (typ.), and the product will enter the static power mode after working for 5S (typ.). The working time and shutdown time can be self-adapted according to different load conditions, which can provide long-term protection and self-recover.




3.7 Over Temperature Protection (OTP)


When the ambient temperature of the power supply exceeds the rated temperature for a period of time, the power supply will turn off the output and enter the hiccup state. After the ambient temperature drops to the set value, the power supply will resume normal operation.

3.8 Output Power Derating


When the input voltage is greater than 100VAC (or 140VDC), only need to derate according to the temperature derating curve;



When the input voltage is lower than 100VAC (or 140VDC), the output power will be derated according to the following input voltage derating curve requirements after the temperature derating.



3.9 Remote Control Switch




ON/OFF (S-5) and SGND(S-6)Switch	Output Status
DC Source power supply voltage is less than 0.8VDC	Normal output
DC Source supply voltage is greater than 4VDC less than 20VDC	Output Off

If the power module is connected to the power supply, the ON and OFF of its output can be controlled by applying an external voltage between the ON/OFF signal pin and SGND.

3.10 DC_OK Signal

The DC_OK signal is used to monitor whether the power supply is working normally, at the first and second pins of the signal terminals. When the output voltage is greater than 90% of the rated output voltage, the DC_OK signal acts, the DC_OK at the output terminal is connected, and LED1 lights up. When the output voltage is less than 85% of the rated output voltage, the DC_OK of the output terminal is disconnected, and LED1 is off.



3.11 Used In Series


The same type of power supply can be connected in series to increase the output voltage. As long as the total output voltage does not exceed 150Vdc, you can connect as many power supplies as you need.Voltages in excess of 60Vdc are no longer considered Safety Extra Low Voltage Circuits (SELV) and can therefore be dangerous. When installing such voltages, it must be protected against touch.

Please avoid generating feedback voltage to the output terminals (eg from a decelerating motor or battery).

Keep a 15mm (left/right) installation gap between the two power supplies and avoid installing the power supplies on top of each other. Do not connect the power supplies in series in an installation orientation other than the standard installation orientation (input terminals down).

Note that leakage current, electromagnetic interference, inrush current and harmonics will increase when multiple power supplies are used.

Refer to the figure below for the wiring method:




3.12 Work In Parallel

The PSU supports 6 PCS in parallel current equalization.

The current sharing bus (PCS) between multiple machines can be short connected to each other, and can be connected by jumper wire.

The output voltage difference of each single module is less than 100mV, which can obtain a better line-end output voltage and current sharing comprehensive effect. The connection mode of the current-sharing function is shown in the figure below:



Note: 1. When used in parallel, the number of parallel modules cannot exceed 6 PCS.

2. When the power modules work in parallel, there is an active current sharing circuit inside to ensure that the current between each module remains balanced.

Active current sharing circuit adopts automatic master-slave current sharing mode. Each power module has a current sharing bus signal (PCS). When working in parallel, the current sharing buses of all power modules must be connected together. It can be connected through jumper wires. The power terminal has reserved two internal connected PCS ports of the current sharing bus signal, namely, two pins of port bit 8 and 9, which can be connected to one of the pins in use.

The output voltage of each power module will affect the current sharing accuracy. The output voltage of the power module is rated voltage ±100mV. In practical applications, if the output voltage value needs to be adjusted, the output voltages of all parallel power modules need to be adjusted to the same voltage. The recommended voltage range is: target voltage value ±100mV.

After the output load of each power module is greater than 50% of the rated load, the current sharing accuracy is required to be ±5%. The calculation formula of current sharing is:

$$\text{Power supply 1's average accuracy} = \frac{Io_1 - (Io_1 + Io_2)/2}{(Io_1 + Io_2)/2} * 100\%$$


$$\text{Power supply 2's average accuracy} = \frac{Io_2 - (Io_1 + Io_2)/2}{(Io_1 + Io_2)/2} * 100\%$$

Io_1: The output current value of the power supply 1 in the parallel power module.

Io_2: The output current value of the power supply 2 in the parallel power module.

3.13 PC Monitoring

In a parallel system, if you need to identify the information of the power modules, you need to monitor each parallel power module by the host computer. The connection diagram is as follows:



That is, connect the RS485-A and RS485-B of the signal terminals to the USB to interface module.

The upper computer "MThings" of Modbus can be used to read and configure the power supply products, or the relevant instructions can be sent directly through the corresponding address.

Function name and corresponding address, quantity and coefficient of ModBus are shown below:

ID	Name	Value	Unit	Read	Command	Write	Block	Address	Count	Offset	Digit	Coefficient
1	SN	20221111001110		Read	--	Write	RW	0	32	0	512	1
2	Product Type	ADHF240-2B-24		Read	--	Write	RW	32	32	0	512	1
3	Firmware Version	3		Read	--	Write	RW	64	1	0	16	1
4	Control Mode	0X0001		Read	--	Write	RW	65	1	0	16	1
5	MODBUS ID	0		Read	--	Write	RW	66	1	0	16	1
6	MODBUS Baud Rate SET	1		Read	--	Write	RW	67	1	0	16	1
7	Run Time	0.381152	h	Read	--	Write	RW	72	2	0	32	0.000277
8	Vo Set	24.000000	V	Read	--	Write	RW	74	2	0	32	1
9	Input Voltage	228.412827	V	Read	--	Write	RW	76	2	0	32	1
10	Output Voltage	24.079004	V	Read	--	Write	RW	80	2	0	32	1
11	Output Current	9.890471	A	Read	--	Write	RW	82	2	0	32	1
12	Output Power	238.158234	W	Read	--	Write	RW	84	2	0	32	1
13	Inside Temperature	84.000000	℃	Read	--	Write	RW	86	2	0	32	1
14	Output State1	0X0003		Read	--	Write	RW	88	1	0	16	1
15	Warning State2	0X0000		Read	--	Write	RW	89	1	0	16	1
16	Remaining Service Life	43676.978848	h	Read	--	Write	RW	90	2	0	32	0.000277
17	Remote ON/OFF	1		Read	--	Write	RW	128	1	0	16	1
18	Running Time from ACON	185	s	Read	--	Write	RW	130	2	0	32	1
19	Output OVP Times	0		Read	--	Write	RW	132	1	0	16	1
20	Output OCP Times	0		Read	--	Write	RW	133	1	0	16	1
21	Input UVP Times	0		Read	--	Write	RW	136	1	0	16	1
22	Input OVP Times	0		Read	--	Write	RW	137	1	0	16	1
23	OTP Times	0		Read	--	Write	RW	138	1	0	16	1

Note: 1. Open the upper computer software, import the configuration, click batch read to obtain the related information. In the command column, input relevant information can be configured, such as the output voltage configuration.

2. Upper computer software index reference.

Input	Norm	Reference point		Unit
	AC input voltage reading accuracy	5		%
Output	Norm	24V	48V	Unit
	Output voltage accuracy	1	1	%
	Output current accuracy	5	5	%
	Adjustable accuracy of key	0.05	0.05	VDC
	Output voltage point	≤35	≤60	VDC
	DCOK signal judgment	≥21.6	≥43.2	VDC

3. The default baud rate is 9600bps. Configure the baud rate as follows.

Configuration instructions	Baud rate (bps)
1	9600
2	38400
3	57600
4	115200

4. After the serial port communication address (ModBus ID) is configured, power off the device and restart it to take effect one minute later.

5. Function and data format definition of MODBUS communication register.

In byte type data 4, the high half word comes first and the low half word comes last

Address	Data Type	Name Of Variable	Function Description	Read And Write Permissions
0-31	Char	SN_MODEL	Product serial number	Read-Only
32-63	Char	Product_MODEL	Product Model Number	Read-Only
64	Uint16	Version	Product firmware version	Read-Only
65	Uint16	control_mode	Control mode: 1: Turn on 600% transient peak current 0: Turns off 600% transient peak current	Read/Write
66	Uint16	Add	Serial communication address (ModBus ID)	Read/Write
67	Uint16	Baud	Baud rate of serial port	Read/Write

			communication	
72 73	Uint32	RUNTIME	Accumulated running time (unit “s”, converted to “h” by the host computer/user)	Read-Only
74 75	Float32	Set_VOL	Output voltage configuration	Read/Write
76 77	Float32	VAC_RMS	AC input voltage	Read-Only
80 81	Float32	Vout	Output voltage	Read-Only
82 83	Float32	Iout	Output current current	Read-Only
84 85	Float32	Pout	Power output	Read-Only
86	Float32	Temperature	Internal temperature	Read-Only
88	Uint16	State1	Output State1 (0~3byte): DC-OK (0), AC-OK (1), OVP (2), OCP (3); 1 for OK or Protection State, 0 for NOK	Read-Only
89	Uint16	State2	Warning State2 (0~5byte): Input UV Warning (1), Input OV	Read-Only

			Warning (2), Remaining Service Life Warning (3), Over Temperature Warning (4), Failure Warning (5); 1 for Warning, 0 for Normal	
90 91	Float32	Life	Remaining Service Life (unit "s", converted to "h" by the host computer/user)	Read-Only
128	Uint16	ON/OFF	Remote ON/OFF, 1 for ON, 0 for OFF	Read/Write
130 131	Uint32	RUNINGTIME	running time (unit "s", converted to "h" by the host computer/user)	Read-Only
132	Uint16	OVP_TIMES	Output OVP Times	Read/Write for Reset to zero
133	Uint16	OCP_TIMES	Output OCP Times	Read/Write for Reset to zero
136	Uint16	INPUT_UVP_TIMES	Input UVP Times	Read/Write for Reset to zero
137	Uint16	INPUT_OVP_TIMES	Input OVP Times	Read/Write for Reset to zero
138	Uint16	OTP_TIMES	OTP Times	Read/Write for Reset to zero


3.14 Back Voltage Load

Loads such as decelerating motors, inductors can feed voltage back into the power supply. This property is also known as feedback voltage resistance or resistance to opposing electromagnetic forces.

ADHF240-2B-24: ① The feedback voltage within 30V, product will not shut down, and it will automatically recover after no feedback voltage in; ②If the feedback voltage exceeds 30V and is less than 35V, the output will be shut down and restart after 5S.

ADHF240-2B-48: ① The feedback voltage within 57V, product will not shut down, and it will automatically recover after no feedback voltage in; ②If the feedback voltage exceeds 57V and is less than 63V, the output will be shut down and restart after 5S.

The power supply is resistant to the voltage that the load feeds back into the power supply and will not fail regardless of whether the power supply is on or off. The following function diagram:



Maximum allowable feedback voltage	
Model	Maximum feedback voltage
ADHF240-2B-24	35VDC
ADHF240-2B-48	63VDC

4. Installation Requirements

4.1 Safety Introduction

WARNING: RISK OF ELECTRIC SHOCK DURING HIGH VOLTAGE WORKING WITH THIS EQUIPMENT

- After the power module is disconnected from the input AC or DC power, leave it for at least one minute

before starting to operate it.

- When installing the input cable to the power module, first connect the ground terminal, and then connect the L and N cables.
- When removing the input wire, first remove the L wire and N wire, and then remove the ground wire
- When disassembling and assembling, make sure that no objects fall into the inside of the power module.
- Be careful of high temperature burns
- After the power module works in a high temperature environment, wait for its shell to cool before operating it.
- This product needs to be installed by professionals and needs to be used with other equipment.


4.2 Safety Requirements

When installing, pay attention to the primary side and the protective ground. The creepage distance and electrical clearance of the primary side and the secondary side meet the safety requirements, refer to EN/UL61010.

4.3 Withstand Pressure Test

The screw at the side mark of the casing should be removed when the product is tested for pressure resistance .

The built-in gas discharge tube protects the power supply from asymmetric interference variables (e.g. EN 61000-4-5). Each power supply sustained voltage test will cause a very high load on the power supply. Therefore, unnecessary load or damage to the power supply caused by high test voltage should be avoided. Disconnect the device's built-in gas discharge tube if necessary to use a higher test voltage. Reconnect the gas discharge tube after successful completion of the test.



Danger: Using the wrong gas discharge tube bolts can result in an electric shock hazard or power supply damage.To connect the gas discharge tube, use only the gas discharge tube bolts originally installed in the power supply.

Disconnect the gas discharge tube by performing the following steps.

1. Disconnect the power supply to the unit ;

2. Completely unscrew the bolt to ensure that the gas discharge tube is connected to a safe position. Now that the gas discharge tube has been disconnected, it no longer functions;


3. Perform sustained voltage test on the power supply;


4. After successful voltage test, screw the gas discharge tube back to the power supply completely.

4.4 Installation Method


Installation direction: When installing, the port of the output end should be upward, and the port of the input end should be downward. (See below)


Note: Pay attention to the temperature rise of the device in different installation modes. Derate the device according to the actual situation.






Various Installation Methods









① Mounting the universal DIN rail power supply.
(Forward Installation. Label is needed to be removed)


② Mounting the universal DIN rail power supply.(Reverse Installation. Label is needed to be removed)




① After connecting the terminal to the connecting wire, lay and align the connecting wire.
② Tie up the stripes with cables and fix the connecting wires through the gaps on the both sides of the shell.





Rotate the installation position
(0° Z-Axis)







Rotate the installation position
(90° Z-Axis)







Rotate the installation position
(180° Z-Axis)







Rotate the installation position
(270° Z–Axis)






Rotate the installation position
(90° X–Axis)





Rotate the installation position
(270° X–Axis)




Materials required in the installation		
1	Product	1PCS
2	Phillips screwdriver Slotted screwdriver	1PCS
3	TS35/7.5 or TS35/15	1PCS
4	24–10AWG Wire	/ PCS
5	The content is for reference only. Regarding the actual wire diameter and tightening torque, refer to the dimensional drawing.	



Product



Phillips screwdriver
Slotted screwdriver
Diameter : 3mm






TS35/7.5 or TS35/15


Installation steps ①-②

①Clamp the buckle of the product into the TS35 DIN rail.




②Push the product vertically towards the TS35 DIN rail until hearing the sound of the buckle snapping into it.

Disassembly Steps③–④



③After inserting the slotted screwdriver into the square groove at the bottom of the buckle, push the slider of the buckle downward in the direction shown in the figure.




④Hold the bottom of the product and push it outwards while pushing down the slider, then lift the product up to take the product out of the DIN rail.

Wiring / Unwiring Steps ⑤–⑥



⑤Turn the Phillips screwdriver to the left to loosen the terminal screws, insert the head of the wire into the bottom of the terminal, and then turn the screwdriver to the right to tighten the terminal screws



⑥Turn the Phillips screwdriver to the left to loosen the terminal screw and pull the wire out of the bottom of the terminal